Windows 8 手動設定連線執行步驟

連線步驟如下:

- 1. 若您使用 32 位元 win 8, 請下載安裝 32bit 版 EAP-GTC 模組 >>download <<
- 2. 若您使用 64 位元 win 8, 請下載安裝 64bit 版 EAP-GTC 模組 >>download <<
- 3. 設定 SSID 連線設定步驟
- 4. 開始連線
- 5. 如果第一次連 NPUST-M 可能會失敗,請再重新連一次。
- 因為 Microsoft 在 Windows 8 版本,取消無線網路 profile 管理介面,若要手動設定管理無線 網路 profile,必須改用命令模式進行。相關的資訊,請參考<<u>Microsoft 官網</u>>之說明。

安裝步驟如下:

Step 1 執行 EAP-GTC 模組 安裝程式:

B EAP-GT	C-x64 - InstallShield Wizard	×
24.	Welcome to the InstallShield Wizard for EAP-GTC-x64	
	The InstallShield(R) Wizard will install EAP-GTC-x64 on your computer. To continue, dick Next.	
	WARNING: This program is protected by copyright law and international treaties.	
	< Back Next > Cancel	

Step 2 選擇 accept 按 next

B EAP-GTC-x64 - InstallShield Wizard	×			
License Agreement Please read the following license agreement carefully.				
Aruba Networks, Inc.	^			
End-User Software License Agreement ("Agreement")				
IMPORTANT YOU SHOULD CAREFULLY READ THE FOLLOWING TERMS BEFORE INSTALLATION OR USE OF ANY SOFTWARE PROGRAMS FROM ARUBA WIRELESS NETWORKS, INC. ("ARUBA"). BY CLICKING "YES" ON THIS SCREEN, YOU INDICATE THAT YOU AGREE TO BE BOUND BY THE TERMS AND CONDITIONS OF THIS AGREEMENT. THEREFORE, PLEASE READ THE TERMS AND CONDITIONS CAREFULLY BEFORE CLICKING ON "YES". IF YOU DO NOT AGREE TO THE TERMS AND CONDITIONS OF THE AGREEMENT, CLICK "NO" ON THIS SCREEN, IN WHICH CASE YOU WILL BE DENIED ACCESS TO THE SOFTWARE. IF THESE	~			
I accept the terms in the license agreement I do not accept the terms in the license agreement InstallShield				
< Back Next > Cancel				

Step 3 選擇 complete 按 next

.₽	EAP-GTC-x64 - InstallShield Wizard
Setup Type Choose the se	etup type that best suits your needs.
Please select a	a setup type.
Complete	All program features will be installed. (Requires the most disk space.)
O Custom	Choose which program features you want installed and where they will be installed. Recommended for advanced users.
InstallShield ———	< Back Next > Cancel

Step 4 選擇 install

EAP-GTC-x64 - InstallShield Wizard	×
Ready to Install the Program The wizard is ready to begin installation.	5
Click Install to begin the installation.	
If you want to review or change any of your installation settings, click Back. Click Cancel to exit the wizard.	
InstallShield	
< Back	

Step 5

₿	EAP-GTC-x64 - InstallShield Wizard 🛛 – 🗖 🗙				
Installing The prog	Installing EAP-GTC-x64 The program features you selected are being installed.				
1 6	Please wait while the InstallShield Wizard installs EAP-GTC-x64. This may take several minutes.				
	Status:				
InstallShield –					
	< Back Next > Cancel				

Step 6 按 finish



Step 7 請重新開機,開完機後執行快速設定檔案

ø	EAP-GTC-x64 Installer Information	×
Í	You must restart your system for the configuration changes made to EAP-GTC-x64 to take effect. Click Yes to restart now or No if you plan to restart later.	
	Yes No	

Step 8 點選螢幕右下角無線網路符號



Step 9 滑鼠右鍵,點選螢幕右下角的網路圖示, 再點選「開啟網路和共用中心」



Step 10 點選「變更網路設定」中的「設定新的連線或網路」



Step 11 點選「手動連線到無線網路」



Step 12 設定內容如下圖所示,建立網路名稱 NPUST_M

「安全性類型」:請選擇 WPA2-Enterprise

「加密類型」:請選擇 AES

			-		×
G .	2 手動連線到無線網路				
ţ	輸入您要新增之無線維	图路的資訊			
쐶	網路名稱(E):	NPUST_M			
\$	安全性類型(S):	WPA2-Enterprise Y			
ħ	加密類型(R):	AES 🗸			
\$	安全性金鑰(C):	隠藏字元(H)			
	✓ 自動啟動這個連線(T)]			
	□即使網路未廣播,還是 警告:若選取此選項,	ŀ進行連線(O) 您電腦的陽私權可能會有風險。			
			_		
		下一步(N)	取》	ğ

Step 13 出現已成功新增 NPUST_M, 請再繼續點選「變更連線設定」



Step 14 請選選「安全性」資料夾,再從「選擇網路驗證方法」

NPUST-M 無線網路內容		×	
連線 安全性			
安全性類型(E): 加密類型(N):	WPA2-Enterprise	¥	
選擇網路驗證方法(O):			
Microsoft: Protected	EAP (PEAP) v	設定(S)	
₩ 每次登入時都記住都 進階設定(D)	我在此連線的認證(R)		
L			
	- E	建定 取消	

項目點選「Microsoft: Protected EAP(PEAP)」後,再點選「設定」

受保護的 EAP 內容 ×
連線時:
透過驗證憑證來確認伺服器身分識別(Ѵ)
■連線到這些伺服器(例如:srv1;srv2;.*\.srv3\.com)(O):
受信任的根憑證授權單位(R):
AddTrust External CA Root
Class 3 Public Primary Certification Authority
DigiCert Assured ID Root CA
DigiCert Global Root CA
DigiCert High Assurance EV Root CA
DST Root CA X3
< >>
連線前的通知(T):
如果無法驗證伺服器的身分識別則告知使用者 >
選擇驗證方法(S):
EAP-Token ✓ 設定(C)
✔ 啟用快速重新連線(F)
☑ 建制網路存取保護(N)
□ 如果伺服器未顯示加密繫結的 TLV 就中斷連線(D)
□ 愈用識別隱私權(I)
確定 取消

Step 15 取消「確認伺服器憑證」 的勾選, 再點選"選擇驗證方法"內「EAP-Token」

Step 16 最後再點選 NPUST_M 連線

網路 ^{飛航模式} 關閉 Wi-Fi	
NPUST_M	atl
✔ 自動連線	
	連線(C)
NPUST	S al
Rentong	Sal
DSL-6641K	ail
ASUS	ail
CHT 2051 wifi	ail
DSL-6740C	ail
BUFFALO-68F0E8	% il
BUFFALO-68F0E8-1	% il



Step 17 輸入使用者和密碼,最後的 logon domain 暫不用輸入。

Step 18 最後可以看到「已經連線」

網路 ^{飛航模式} 關閉	
Wi-Fi	
NPUST_M	已連線
NPUST	Sul.
Rentong	Sal
BUFFALO-68F0E8-1	20
BUFFALO-68F0E8	20
CHT 2051 wifi	atl
DSL-6641K	atl
DSL-6740C	ati